



Alan Chern

Systems and PC boards that use FPGAs and ASICs are often very densely populated with components and ICs. This dense real estate (especially the supporting circuitry for FPGAs, such as DC/DC regulators) puts a burden on system designers who aim to simplify layout, improve performance and reduce component count. A new family of DC/DC μ Module[®] regulator systems with multiple outputs is designed to dramatically reduce the number of components and their associated costs. These regulators are designed to eliminate layout errors and to offer a ready-made complete solution. Only a few external components are needed since the switching controllers.

The LTM®4619 switching DC/DC μ Module converter regulates two 4A outputs from a single wide 4.5V to 26.5V input voltage range. Each output can be set between 0.8V and 5V with a single resistor. In fact, only a few components are needed to build a complete circuit (see Figure 2).

Figure 2 shows the LTM4619 μ Module regulator in an application with 3.3V and 1.2V outputs. The output voltages can be adjusted with a value change in R_{SET1} and R_{SET2} . Thus, the final design requires nothing more than a few resistors and capacitors. Flexibility is achieved by pairing outputs, allowing the regulator to form different combinations such as single input/dual independent outputs or single input/parallel single output for higher maximum current output.



LT, LT, LTC, LTM, Linear Technology, the Linear logo, Burst Mode and μ Module are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.




Figure 2. 4.5V to 26.5V Input to Dual 3.3V and 1.2V Outputs with 4A Maximum Output Current Each

The efficiency of the system design for Figure 2 is shown in Figure 3 and power loss is shown in Figure 4, both at various input voltages. Efficiency at light load operation can be improved with selective pulse-skipping mode or Burst Mode® operation by tying the mode pin high or leaving it floating.

Multiphase Operation for Four or More Outputs

For a 4-phase, 4-rail output voltage system, use two LTM4619s and drive their MODE_PLLIN pins with a LTC®6908-2 oscillator, such that the two μ Module devices are synchronized 90° out of phase. Reference Figure 21 in the LTM4619 data sheet. Synchronization also lowers voltage ripple, reducing the need for high voltage capacitors whose bulk size consumes board space. The design delivers four different output voltage rails (5V, 3.3V, 2.5V and 1.8V) all with 4A maximum load.

Thermal Performance

Exceptional thermal performance is shown in Figure 5 where the unit is operating in parallel output mode; single 12V_{IN} to a single 1.5V_{OUT} at 8A. Both outputs tied together create a combined output current of 8A with both channels running at full load (4A each). Heat dissipation is even and minimal, yielding good thermal results. If additional cooling is needed, add a heat sink on top of the part or use a metal chassis to draw heat away.

Conclusion

The LTM4619 dual output μ Module regulator makes it easy to convert a wide input voltage range (4.5V to 26.5V) to two or more 4A output voltage rails (0.8V to 5V) with high efficiency and good thermal dissipation. Simplicity and performance are achieved through dual output voltage regulation from a single package, making the LTM4619 an easy choice for system designs needing multiple voltage rails.




Figure 3. Efficiency of the Circuit in Figure 2 at Different Input Voltage Ranges for 3.3V and 1.2V Outputs




Figure 4. Power Loss of the Circuit in Figure 2 at Different Input Voltages for 3.3V and 1.2V Outputs




Figure 5. LTM4619: Exceptional Thermal Performance of a Paralleled Output μ Module Regulator (12V_{IN} to Paralleled 1.5V_{OUT} at 8A Load)

Data Sheet Download

www.linear.com

For applications help,
call (408) 432-1900, Ext. 2593

Linear Technology Corporation
1630 McCarthy Blvd., Milpitas, CA 95035-7417
(408) 432-1900 • FAX: (408) 434-0507 • www.linear.com

dn474 LT/TP 1110 116K • PRINTED IN THE USA

LINEAR
TECHNOLOGY
© LINEAR TECHNOLOGY CORPORATION 2009